

June 2015

Multilayer Band Pass Filter

For 2400-2500MHz

DEA162450BT-2092A1-H

- 1.6x0.8mm [EIA 0603]*
- * Dimensions Code JIS[EIA]

Caution

The products in this catalog will be or have been stopped production

Discontinue Issue Date	Jun. 3, 2022	
Last Purchase Order Date	Mar. 31, 2023	
Last Shipment Date	Mar. 31, 2024	

Please refer to our Web site about replacement information.



Conformity to RoHS Directive

Multilayer Band Pass Filter

For 2400-2500MHz

DEA162450BT-2092A1-H


[Bottom view] 1.60±0.15 0.60max. 0.60max. 0.20min. Terminal functions 1 IN 2 GND 3 GND

■ RECOMMENDED LAND PATTERN

0.20min.

1.60 0.50 1.10 Dimensions in mm

EVALUATION BOARD



ORAMS Directive Compliant Product: See the following for more details related to RoHS Directive compliant products. http://product.tdk.com/en/environment/rohs/

Dimensions in mm

[•] All specifications are subject to change without notice.

[•] Before using these products, be sure to request the delivery specifications.



DEA162450BT-2092A1-H

ELECTRICAL CHARACTERISTICS

Item	Frequency Range (MHz)	Min.	Тур.	Max.
Insertion Loss (dB)	2400 to 2500	_	2.74	3.2
	2400 to 2500	_	-/	3.5 (-40 to +85°C)
Return Loss (dB)	2400 to 2500	10	/	7 /-
Attenuation (dB)	880 to 915	40		_
	1710 to 1850	40	_	_
	1850 to 1910	40	_	_
	1920 to 1990	40	_	_
	2110 to 2170	35	- O	_
	4800 to 5000	30		_
	7200 to 7500	30	-	_
Characteristic Impedance (Ω)			50 (Nominal)	

[•] Ta: +25±5°C

TEMPERATURE RANGE

Operating temperature	Storage temperature	
(°C)	(°C)	
-40 to +85	-40 to +85	



All specifications are subject to change without notice.Before using these products, be sure to request the delivery specifications.




6500

7500

DEA162450BT-2092A1-H

■ FREQUENCY CHARACTERISTICS


□INSERTION LOSS





3500 4500 Frequency(MHz)


RETURN LOSS



[•] All specifications are subject to change without notice.

[•] Before using these products, be sure to request the delivery specifications.

■ RECOMMENDED REFLOW PROFILE



Preheating		Soldering				
		Critical zone (T3 to T4)		Peak		
Temp.		Time	Temp.	Time	Temp.	Time
T1	T2	t1	Т3	t2	T4	t3*
150°C	200°C	60 to 120sec	217°C	60 to 120s	sec 240 to 260°C	30sec max.

*t3: Time within 5°C of actual peak temperature

The maximum number of reflow is 3.

- All specifications are subject to change without notice.Before using these products, be sure to request the delivery specifications.



REMINDERS FOR USING THESE PRODUCTS

Before using these products, be sure to request the delivery specifications.

SAFETY REMINDERS

Please pay sufficient attention to the warnings for safe designing when using these products.

⚠ REMINDERS

The products listed on this catalog are intended for use in general electronic equipment, telecommunications equipment, home appliances, amusement equipment, computer equipment, personal equipment, office equipment, measurement equipment, industrial robots) under a normal operation and use condition.

The products are not designed or warranted to meet the requirements of the applications listed below, whose performance and/or quality require a more stringent level of safety or reliability, or whose failure, malfunction or trouble could cause serious damage to society, person or property.

Please understand that we are not responsible for any damage or liability caused by use of the products in any of the applications below or for any other use exceeding the range or conditions set forth in this catalog.

- (1) Aerospace/Aviation equipment
- (2) Transportation equipment (cars, electric trains, ships, etc.)
- (3) Medical equipment
- (4) Power-generation control equipment
- (5) Atomic energy-related equipment
- (6) Seabed equipment
- (7) Transportation control equipment

- (8) Public information-processing equipment
- (9) Military equipment
- (10) Electric heating apparatus, burning equipment
- (11) Disaster prevention/crime prevention equipment
- (12) Safety equipment
- (13) Other applications that are not considered general-purpose applications

When using this product in general-purpose applications, you are kindly requested to take into consideration securing protection circuit/ equipment or providing backup circuits, etc., to ensure higher safety.

- All specifications are subject to change without notice.
- Before using these products, be sure to request the delivery specifications.