E-Series RF 1:4 Transformer 3 - 800 MHz

Features


- 1:4 Impedance Ratio
- Surface Mount Package
- Tape and Reel Packaging Available
- RoHS* Compliant & 260°C Reflow Compatible

Description

The MABA-009488-61HWCA is a RoHS compliant 1:4 RF flux coupled transformer in a surface mount package.

Typical applications include single to balanced mode conversion.

Schematic



Pin Configuration

Pin #	Function	Pin #	Function
1	Secondary	4	Primary Dot
2	Secondary CT	5	Primary
3	Secondary Dot		

Electrical Specifications: Freq. = 3 - 800 MHz, $T_A = 25^{\circ}C$, $Z_0 = 50 \Omega$, $P_{IN} = 0 \text{ dBm}$

Parameter	Freq. Test Conditions (MHz)	Units	Min.	Тур.	Max.
Insertion Loss	3 - 400 400 - 800	dB	_	0.6 1.5	1 3
Amplitude Balance	3 - 400 400 - 800	dB	_	0.1 0.7	0.5 1.5
Phase Balance	3 - 400 400 - 500	0	—	0.3 3.0	3 10
Input Return Loss	3 - 400 400 - 800	dB	13 10	22 11	30 13

Ordering Information

Parameter	Package	
MABA-009488-61HWCA	2000 piece reel	

Absolute Maximum Ratings

Parameter	Absolute Maximum	
RF Power	250 mW	
DC Current	240 mA	
Operating Temperature	-40°C to +85°C	

1



Rev. V5

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.




Rev. V5


E-Series RF 1:4 Transformer 3 - 800 MHz


Typical Performance Curves at +25°C

Insertion Loss




Amplitude Balance





Phase Balance




2

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macom.com for additional data sheets and product information.


E-Series RF 1:4 Transformer 3 - 800 MHz

Outline Drawing



* Dimensions are millimeters ±0.38 unless otherwise specified.

Carrier Tape Orientation



Tape & Reel Information

Parameter	Units	Value		
Qty per reel	-	900		
Reel Size	mm	330		
Tape Width	mm	12.00		
Pitch	mm	8.00		
Orientation	-	F31		
Reference Application Note ANI-019 for orientation				

3

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.



Rev. V5

MACOM

E-Series RF 1:4 Transformer 3 - 800 MHz

Rev. V5

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

4

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.